

External receiver wiring

Turn power to garage door opener off then connect wires to the terminals on your garage door opener as per below

Large Red : 12-24V
Large White : Negative
Small Black : Negative



Switch power back on.

Pair the remote using top (#1) button by pressing the learn button on the receiver briefly and then the (#1) remote button twice.

Connect the below wire to PB terminal dependant on which remote button you would like to use to operate the device

Blue : Remote button 4

Red : Remote button 3

Yellow : Remote button 2

White : Remote button 1